

7" Touch Monitor white, 2-wire for door intercom

Art.-Nr. TVHS21210

Seite 1 von 2



TOTAL MODULAR: THE VIDEO INTERCOM SYSTEM

See people in front of the door, talk to them, open the door. Easy to install, modularly adaptable to any building - and easy to operate on the monitor.

See everything, intercom, just open the door

The 7" touch monitor is the indoor station for operating the ModuVis door intercom. It displays the live pictures of the video module (and other cameras) and allows intercom in high speech quality. The door is opened by touch - via the door opener (door buzzer) connected to the video module. The monitor has an internal memory for recording scenes.

Operating convenience local & on the road: via monitor & App

Operation is either via the stationary touch monitor or mobile on the smartphone/tablet using ABUS Link Station App.

2-wire installation

Communication between the 2-wire monitor, video module and other modules is via a 2-wire distributor (converter unit). IP/PoE/WLAN variant: see TVHS20200.

Totally modular, extensively expandable

A clear advantage: Depending on requirements, the ModuVis system can be used to create up to 49 flats - with one monitor per flat. The added security: Up to 16 IP cameras can be integrated for video surveillance and displayed on the monitor. Whichever variant of monitor and video module (2-wire or IP/PoE/WLAN) is selected - the systems are compatible with each other.

Technologies

7" Touch Monitor white, 2-wire for door intercom

Art.-Nr. TVHS21210

Seite 2 von 2

- Indoor station for the FaceXess/ModuVis door intercom system
- Simple operation and communication in very good voice and picture quality within the door intercom system
- Live image display of the video module or of up to 16 network cameras (IP/WLAN)
- Intercom and react (e.g. opening the door) when someone rings the bell
- Recording on internal memory (expandable with MicroSD card)
- Save and display pictures of missed people who rang the bell.
- Connection for already existing door gong
- Relay output for door opener of the flat floor door
- Digital input for floor bell push button
- Including wall bracket (mounting plate)

Technical data - 7" Touch Monitor white, 2-wire for door intercom

Alarm output	2 (2A@30VDC / 0.5A@125AC)
Audio	Built-in microphone and speaker
Compatible with ABUS Link Station	Yes
Connections	1 x DC/Audio/Video, 1 x switching input, 2 x alarm output
DC voltage supply	over TVHS21310 V
Dimensions	200 x 140 x 15 mm
Display	7" Touchscreen Monitor
Display surface	Touch-Screen
Height	140 mm
Length	15 mm
Max. humidity	90 %
Max. operating temperature	55 °C
Microphone	Yes
Min. operating temperature	-10 °C
Network camera protocols	TCP/IP, RTSP
PSTI conformity given	Yes
PSTI conformity required	Yes
Power consumption	6 W
Resolution live view	1.024 x 600 Pixel TVL
Storage medium	microSD card, 32 GB (option)
Width	200 mm