

# Secvest 2WAY Wireless Panic Alarm Transmitter

Art.-Nr. FU8305

Seite 1 von 2



The Secvest wireless panic alarm transmitter is a handheld detector of the Secvest (or the Terxon with a wireless expansion module). With a press of a button, you can easily and discreetly trigger a robbery alarm if you need help. With a weight of 14 grams and dimensions of 44 x 32 x 13 mm, the wireless panic transmitter fits in any pocket. The sender is assigned to a specific Secvest user. One press of a button suffices to trigger a robbery alarm, even when the system is disarmed. In the system settings of the Secvest you can determine whether it is a local or silent alarm. The wireless panic alarm transmitter can be fastened onto an arm band or belt or you can wear it around your neck. The transmitter is protected against spraying water (protection class IP65) and can even be worn in the shower. Is not compatible with the FUAA50000.

## Technologies

- For discreet triggering of a panic alarm
- Compact and easy to use
- Water spray resistant (IP65)
- Can be attached to the arm, belt, or around the neck

## Technical data - Secvest 2WAY Wireless Panic Alarm Transmitter

Battery - max. battery life	5 y
Colour	black
Compatible with	Secvest, Terxon
DC voltage supply	3 V
Dimensions	(WxHxD) 44x32x13 mm
Environmental class	II
Height	32 mm
Housing material	ABS
IP protection class	65
Length	13 mm
Max. operating temperature	55 °C
Max. transmission range (building)	30 m

# Secvest 2WAY Wireless Panic Alarm Transmitter

Art.-Nr. FU8305

Seite 2 von 2

## Technical data - Secvest 2WAY Wireless Panic Alarm Transmitter

Max. transmission range (free field)	100 m
Min. operating temperature	-10 °C
Modulation	FM
Net weight	0,01 kg
PSTI conformity required	No
Radio frequency	868,6625 MHz
Radio power	10 mW
Security level	2
VdS class	none
Voltage monitoring	Yes
Width	44 mm