

Secvest Wireless Indoor Siren

Art.-Nr. FUSG50010

Seite 1 von 2



Reliable warning for indoor areas

The Secvest wireless indoor sounder is an optional Secvest accessory. As a purely acoustic sounder, it supports the wireless outdoor sounder and Secvest alarm panel with a signal tone of 90 dB sound pressure in the event of an alarm. The sounder and alarm panel communicate at 868.6625 MHz, a wireless frequency exclusively reserved for the security industry. The wireless indoor sounder can be powered by battery or a power supply unit. If batteries are used, the sounder has a service life of approx. 2 years. The sounder indicates when the battery life is coming to an end.

Technologies

- Designed to support of the alarm panel and wireless outdoor sounder acoustically
- Loud sounder (90 dB(A)@1 m)
- 12 V external power supply for operation without batteries (optional)
- Any number of indoor sirens can be integrated into the Secvest wireless alarm system

Technical data - Secvest Wireless Indoor Siren

Battery - max. battery life	2 y
Battery - type	3x 1.5V LR20 battery
Connections	12V
DC voltage supply	4,5/12 V
Dimensions	(WxHxD) 122x208x60 mm
Environmental class	II
Height	208 mm
Housing material	ABS
IP protection class	40
Installation location	Indoors
Length	60 mm

Secvest Wireless Indoor Siren

Art.-Nr. FUSG50010

Seite 2 von 2

Technical data - Secvest Wireless Indoor Siren

Max. humidity	75 %
Max. operating temperature	50 °C
Max. receiving range (building)	30 m
Max. receiving range (free field)	100 m
Min. operating temperature	-10 °C
Modulation	FM
Net weight	0,984 kg
PSTI conformity required	No
Radio frequency	868,6625 MHz
Sound pressure	90 dB
Voltage monitoring	Yes
Width	122 mm