

# Comfion Wireless-Remote-Control

Art.-Nr. FUBE80010

Seite 1 von 2



Operate alarm system, query status, trigger alarm in an emergency: simply with the handy remote control

The mini hand-held transmitter is always with you

To arm and disarm the Comfion alarm system when you come and go, you always have the small remote control with you. The coin-sized hand-held transmitter also serves as a key fob.

Three freely programmable buttons

Three buttons can be individually assigned on the remote control: for example, for activation, deactivation and "internal activation" (system armed, residents in the house), or for home automation (garage door, light control, smart home scenario). The buttons are programmed by a specialist dealer.

Clearly understandable, multi-colored status LED

The multi-colored status LED clearly indicates when the system status has been changed (activated, deactivated, partially armed, fault). The status can also be queried at any time at the touch of a button.

Quick help in an emergency

Use the panic button to trigger an immediate hold-up alarm to get help quickly (e.g. from a connected security service).

Secure radio and 300m range

The securely encrypted radio connection offers a high level of protection against tampering. The range of up to 300m (free field) also allows operation from a distance (garden, driveway).

## Technologies

- Mini wireless remote control for arming/disarming the Comfion wireless alarm panel: very small, light and handy as a key fob
- 3 freely programmable buttons, e.g. for arming/disarming or for switching previously set smart home scenarios
- Multicolored status LED provides information at a glance about the command being executed (activated, deactivated, partially armed, fault)

# Comfion Wireless-Remote-Control

Art.-Nr. FUBE80010

Seite 2 von 2

- Secure radio connection to the Comfion alarm control panel, with a range of up to 300 m (free field) and high tamper/data protection as in online banking (AES128 encryption)
- Maintenance-friendly wireless component, battery life up to 1 year
- Mini hand-held transmitter or radio key, as small as a coin

## Technical data - Comfion Wireless-Remote-Control

Battery - battery operation	Yes
Battery - max. battery life	1 y
Battery - quantity	1
Battery - type	CR2032
Certifications	EN 50131 Grade 2
Compatible with	Comfion
Dimensions	40 x 10 mm
Display	LED
EN	Level 2
Environmental class	II
Gross weight	0,012 kg
Height	10 mm
Housing material	Plastic
Max. receiving range (free field)	300 m
Max. transmission range (free field)	300 m
Modulation	2FSK
Radio frequency	868 MHz
Radio power	25 mW
Sabotage monitoring	No
Security level	2
Voltage monitoring	Yes
Width	40 mm