

Art.-Nr. FUAA45000 Seite 1 von 4



Reliable security. Every day

Want to protect your home from break-ins with modern tools? The Smartvest Pro wireless alarm system is just what you're looking for.

At night, when you step out to shop or spend two weeks away - your home is always reliably & cleverly protected with the Smartvest Pro wireless alarm system: the loud integrated indoor siren sends intruders running, while you get a push notification via the Smartvest Pro app.

All devices take no time to install due to wireless communication. All the control panel needs is a free socket. Timeless design blends into any home's ambience.

With the control panel, the starter set also includes core components: Magnetic contact secures any door or window against intruders. Remote control turns alarm system on/off like the free phone app.

Break-in protection, fire safety & much more

The Smartvest Pro app is also the hub of the security system. With it, you can add whatever other devices you need: practical danger detectors protect against fire and water damage, for example. Smart surveillance cameras deliver live images to every smartphone and tablet connected to your system. A clever lock drive on the front door automatically disarms the alarm system - you don't need a key when coming home anymore. Voice assistants can be integrated, e.g. to arm the alarm system.

The decision is easy: The Smartvest Pro wireless alarm system and all its components are ready to use round the clock. For a comfortably secure home. For you and your family.



Art.-Nr. FUAA45000 Seite 2 von 4

Technologies

- Starter set for the Smartvest Pro wireless alarm system: with control panel including integrated indoor siren, magnetic contact, remote control and free Smartvest Pro app for smartphones and tablets
- Effectively deters burglars with a high-volume alarm and additional, visible outdoor components before they even make it inside (surveillance cameras/outdoor siren)
- Always have full control in an emergency: Push notifications and app on your mobile phone or tablet show you all reported events (with security camera including live stream)
- Smartvest Pro app as the central control hub: Arm/disarm the alarm system (also when out and about), call up the event list/memory, conveniently set up alarm, camera and door scenarios as required (no subscription required)
- Well prepared: for self-installation (even without prior knowledge) lalarm panel can be integrated into the home network via LAN/WiFi (guided by the app)
- For all family members: Control the alarm system from a smartphone, tablet, remote control, with optional code entry or chip key (see keypad), start scenarios e.g. using voice assistant
- Outstanding protection: Control panel/intruder alarm protected against tearing off/tampering, battery operation in the event of a power failure, optional mobile communication module (switches on when the Internet/WiFi/LAN fails)
- Clever expansion: more magnetic contacts, compatible vibration detectors, smoke and water detectors, smart door locks (control alarm system automatically), practical surveillance cameras and much more
- Helpful everyday scenarios: e.g. turn lights and electrical appliances on/off via wireless socket
- Reliable security for your home: Day and night, comfortably secure

Technical data - Smartvest Pro wireless alarm system and app — alarm control panel

AC voltage supply	100 - 240 V
Alarming	Push notification / Acoustic warning signal
Backup power supply	Yes
Battery - GRS type	18650
Battery - battery operation	Yes
Battery - quantity	2
Battery - runtime	max. 20 hrs.
Battery - type	18650 Lithium Rechargable Battery
Colour	white
DC voltage supply	5 V
Dimensions	195 x 130 x 34 mm
Display	LED
Gross weight	0,756 kg
Height	34 mm
Housing material	Plastic
Integrated siren	< 90 dB
Length	195 mm



Art.-Nr. FUAA45000 Seite 3 von 4

Technical data - Smartvest Pro wireless alarm system and app — alarm control panel

Max. humidity	80 %
Max. operating temperature	40 °C
Min. humidity	10 %
Min. operating temperature	0 °C
Net weight	0,54 kg
Network access	RJ-45 connector / WI-FI (10/100 Mbps)
Number of events	1.000
Number of wireless zones	32
Plug type	DC-plug: 3,5 x 1,35mm
Radio frequency	868,3 MHz
Radio modulation	FSK
Software	App: Smartvest Pro
Supported IP cameras	ABUS PPIC31020, PPIC42520, PPIC44520, PPIC46520, PPIC9100, PPIC52520, PPIC54520
Transmission power	11,3 dBm
Width	130 mm
Wireless range	Depending on installation max. 100 m
EAN	4003318867798

Technical data - Smartvest Pro wireless opening detector

EAN	4003318419089
Wireless range	Depending on installation max. 100 m
Transmission power	11.3 dBm
Radio modulation	FSK
Radio frequency	868,3 MHz
Power consumption	0,014 mA
Net weight	0,055 kg
Min. operating temperature	0 °C
Min. humidity	10 %
Max. operating temperature	40 °C
Max. humidity	80 %
Housing material	Plastic
Gross weight	0,088 kg
Dimensions	78 x 28 x 11 mm
Colour	white
Battery - type	CR2032 (3V)
Battery - quantity	1
Battery - max. battery life	1 y
Battery - battery operation	Yes
Area of application	Interior



Art.-Nr. FUAA45000 Seite 4 von 4

Technical data - Smartvest Pro wireless remote control

Area of application	Interior
Battery - battery operation	Yes
Battery - max. battery life	1 y
Battery - quantity	1
Battery - type	CR2032 (3V)
Battery type	Replaceable
Colour	white
Dimensions	69,5 x 28 x 8 mm
Display	LED
Gross weight	0,031 kg
Housing material	Plastic
IP protection class	20
Max. humidity	80 %
Max. operating temperature	40 °C
Min. humidity	10 %
Min. operating temperature	0 °C
Net weight	0,013 kg
Radio frequency	868,3 MHz
Radio modulation	FSK
Standby power consumption	0,01 mA
Transmission power	11,3 dBm
Wireless range	max. 100 m
EAN	4003318419010