

Smartvest Pro wireless opening detector

Art.-Nr. FUMK45000

Seite 1 von 2



Surveillance for doors and windows

Small and discreet, magnetic contacts keep reliable watch over every door and window they are placed on. immediately reporting any unauthorised opening. They can also be used however you need for practical everyday scenarios.

If an unauthorised person tries to get into your home, they will always try to enter through a window or door. Whether at night while you're at home or during the day while you're out, if the Smartvest Pro wireless alarm system is armed, then a Smartvest Pro wireless magnetic contact will register any unauthorised opening and immediately trigger an alarm. This also sends out a push notification to all connected users via the Smartvest Pro app.

So your best bet is to fit detectors on any window or door that an intruder can reach. Don't forget about "climbing aids", such as dustbins, that can create quick access to an upper floor and that side doors through the cellar and garage need to be protected, too.

Not only is this smart magnetic contact helpful in an emergency, it also cuts a fine figure in day-to-day life: you can use it when you come home, for example, to switch on a standard floor lamp automatically using a Smartvest Pro wireless socket, available separately. The battery is long-lasting and easy to replace. For a comfortably secure home. For you and your family.

Technologies

- Placed on the window, front door, patio door and more, Smartvest Pro wireless magnetic contacts reliably detect and report any unauthorised opening
- For protection against burglary and theft
- Triggers the alarm and starts all the custom scenarios configured in combination with the Smartvest Pro wireless alarm system

Smartvest Pro wireless opening detector

Art.-Nr. FUMK45000

Seite 2 von 2

- Optional comfort function, e.g. "if the cellar door opens, then the light is turned on" in combination with the Smartvest Pro wireless socket and a standard floor lamp
- Small and inconspicuous, consists of two parts: one for the window frame or door frame and one for the sash or door leaf
- Easy installation (with adhesive pad or screws, included)
- Includes easily replaceable battery

Technical data - Smartvest Pro wireless opening detector

Area of application	Interior
Battery - battery operation	Yes
Battery - max. battery life	1 y
Battery - quantity	1
Battery - type	CR2032 (3V)
Colour	white
Dimensions	78 x 28 x 11 mm
Gross weight	0,088 kg
Housing material	Plastic
Max. humidity	80 %
Max. operating temperature	40 °C
Min. humidity	10 %
Min. operating temperature	0 °C
Net weight	0,055 kg
Power consumption	0,014 mA
Radio frequency	868,3 MHz
Radio modulation	FSK
Transmission power	11.3 dBm
Wireless range	Depending on installation max. 100 m