

# Secvest Wireless Panic Alarm Button

Art.-Nr. FUAT50010

Seite 1 von 2

Rapid and discreet help when panic sets in

The Secvest wireless panic alarm button is a detector in the Secvest wireless alarm system. At the touch of a button, a panic alarm can be easily and discreetly triggered to summon rapid assistance when it's needed. This alarm works even when the alarm panel is not armed.

Loud alarm or silent alert

You can decide for yourself whether a loud alarm is triggered locally or whether emergency services are silently notified. The optimal locations for the wireless panic alarm button are bedrooms and entrances, or under a sales counter.

## Technologies

- Suitable for discreet alarm triggering which does not attract attention
- It can be mounted under a counter, for example
- Tamper monitoring

## Technical data - Secvest Wireless Panic Alarm Button

Battery - max. battery life	2 years(s)
Battery type	Lithium battery – CR2477N
Colour	white
Compatible with	Secvest, Terxon, BUM060040
DC power supply	3 V
Depth	52 mm
Diameter	85 mm
Dimensions	(WxHxD) 85x85x52 mm
Environmental class	II
Height	85 mm
Housing material	Thermoplastic material
Length	52 mm
Max. Operating temperature	50 °C
Max. Transmit range (free field)	100 m
Max. Transmitting range (building)	30 m
Mechanical protection	No
Min. operating temperature	-10 °C
Modulation	FM
Net weight	0.17 kg

# Secvest Wireless Panic Alarm Button

Art.-Nr. FUAT50010

Seite 2 von 2

## Technical data - Secvest Wireless Panic Alarm Button

PSTI conformity needed	No
Product group	Detectors
Protection class IP	32
Radio alarm bandwidth	Narrow band
Radio frequency	868.6625 MHz
Security gradient	2
Technology	Electronics
Touchpanel	No
Type of protection	other warning devices
VdS class	without
VdS recognized	No
WEEE group	09
width	85 mm